


D9127 Series POPIT Modules

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Provides point identification of initiating devices
- ▶ Supervises wiring to devices for circuit integrity
- ▶ Expands the number of points in the system
- ▶ Compact size
- ▶ Terminal connections for reliability

The D9127 Series POPIT Modules includes the D9127T (with magnetic tamper switch) and the D9127U (without tamper). They are used with a D8125 Addressable Expansion Module when there is a need to expand a compatible control panel beyond its standard number of on-board initiating zones or points. Future system expansion is very economical as D9127 Series POPITs can be added anywhere along the two-wire data expansion loop from the D8125 module.

Both modules include proven technology that combines zone and point supervision with individual device addressing on one pair of wires. Screw terminals provide reliable connections for the data expansion loop and supervised sensor loop wiring. Install a 33 kΩ end-of-line resistor at the farthest point on the loop for proper supervision. The units are small and easily installed in standard outlet boxes, above false ceilings, closets, or other accessible locations.

Certifications and approvals

Australia C-Tick

Region	Certification	
USA	UL	AMCX: Central Station Alarm Units (UL1610, UL1635), AMCX7: Central Station Alarm Units Certified for Canada (cULus), AOTX: Local Alarm Units (UL464, UL609), AOTX7: Local Alarm Units Certified for Canada (cULus), APAW: Police Station Alarm Units (UL365, UL464), APAW7: Police Station Alarm Units Certified for Canada (cULus), APOU: Proprietary Alarm Units (UL1076), APOU7: Proprietary Alarm Units Certified for Canada (cULus), NBSX: Household Burglar Alarm System Units (UL1023), NBSX7: Household Burglar Alarm System Units Certified for Canada (cULus), UOJZ: Control Units, System (UL864, 9th edition), UTOU: Control Units and Accessories - Household System Type (UL985), UTOU7: Control Units and Accessories - Household System Type Certified for Canada (cULus)
	FM	
	NYC-MEA	12-92-E, Vol.12 12-92-E, Vol. 12
	NYC-MEA	12-92-E, Vol. 15 12-92-E, Vol. 15

Region	Certification	
	FDNY-CoA	6059
	CSFM	7167-1615:0100 CONTROL UNIT (HOUSEHOLD)
	CSFM	7165-1615:0113 FIRE ALARM CONTROL UNIT (COMMERCIAL)
	CSFM	7167-1615:0243
	CSFM	7165-1615:0119

Installation/configuration notes

Compatibility Information

Control Panels All G Series control panels, D9412, D7412, D7212, D7212B1, D9112, D9112B1, D8112G1, D8112G2, and D9124

Module D8125

The D8125 Multiplex Zone Expander is required. The D9127 modules are wired in parallel on the D8125 data loop.

Number of POPIT Modules per Control Panel

D7212G, D7212GV2, D7212GV3	32 D9127 POPITs
D7212B1	40 D9127 POPITs
D7212, D7412, D7412G, D7412GV2, D7412GV3	67 D9127 POPITs
D9124	119 D9127 POPITs
D9112B1	126 D9127 POPITs
D9112, D9412, D9412G, D9412GV2, D9412GV3	238 D9127 POPITs

Wiring Considerations

Wire Size	Maximum Length of all Data Expansion Loops Combined
0.8 mm (22 AWG)	549 m (1800 ft)
1.0 mm (20 AWG)	881 m (2890 ft)
1.2 mm (18 AWG)	1402 m (4600 ft)
1.5 mm (16 AWG)	2231 m (7320 ft)
1.8 mm (14 AWG)	3551 m (11650 ft)

D8125 to POPIT Loops

Use one two-wire data expansion loop, or distribute the POPITs on up to three loops. The maximum lengths shown in the following table are for all data expansion loops combined connected to the same D8125 module. Setting DIP switches on the POPIT modules assigns them to point numbers. The switch setting on each POPIT assigns it a point number, regardless of its physical location.

POPIT to Sensor Loops

The number of detection devices each sensor loop can supervise is limited only by the resistance on the loop. Resistance on each sensor loop must be less than 100 Ω not including the end-of-line (EOL) resistor. Certain UL and National Fire Protection Association (NFPA) applications can limit the number of detection devices. Consult the appropriate UL or NFPA standards.

Terminate each POPIT sensor loop with the 33 k Ω EOL resistor included with each POPIT.

Use a twisted-pair wire (six twists per foot) in all POPIT installations for both the data expansion loop wiring and the POPIT sensor loops. Run wires away from AC sources to prevent AC induction.

Parts included

Quantity	Component
1	POPIT module
1	33 k Ω EOL resistor
1	Magnet (D9127T only)
1	Hardware pack
1	Literature pack

Technical specifications

Environmental Considerations

Relative Humidity:	Up to 93% non-condensing
Temperature (operating):	0°C to +50°C (+32°F to +122°F)

Properties

Color:	Off white
Dimensions:	8.1 cm x 3.8 cm x 2.4 cm (3.2 in. x 1.5 in. x 0.9 in.)
Material:	UL Listed fire-resistant

Power Requirements

Current Draw	0.8 mA maximum
Resistance:	Maximum increase in resistance on the POPIT loop is 1000 Ω . Maximum resistance between the D8125 module and each POPIT is 90 Ω .
Voltage (operating):	12 VDC nominal

Sensor Loop

Resistance:	Maximum resistance on the sensor loop is 100 Ω .
Response Time:	1 sec approximately

Ordering information

Accessories

D9127T POPIT Module

Includes a magnetic tamper switch.

Order number **D9127T**

D9127U POPIT Module

No tamper switch.

Order number **D9127U**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com