












Bulletin 140M Motor Circuit Protectors

Introduction Standards Compliance and Certifications Quick Selection Cat. No. Explanation Product Selection



Typical Wiring Diagram(s) Application Ratings Accessories Specifications Approximate Dimensions

Description		Operator Position *			Term. No.	Description	Connection Diagram ‡	For Use With	Cat. No.
		OFF	ON	Tripped					
	Front-Mounted Auxiliary Contact <ul style="list-style-type: none"> 1-pole or 2-pole No additional space required Only 1 per device 	O	X	O	13-14	N.O. Aux		140M-C, D, F; 140U-D (UL489 only in combination with 140M-C-AFC)	140M-C-AFA10
		X	O	X	11-12	N.C. Aux			140M-C-AFA01
	Right Side-Mounted Auxiliary Contact <ul style="list-style-type: none"> 2-pole Adds 9 mm to the width of the device Two per MPCB 	O	X	O	13-14	N.O. Aux		140M-C, D, F; 140U-D (UL489 only in combination with 140M-C-AFC)	140M-C-AFA11
		X	O	X	21-22	N.C. Aux			
		O	X	O	13-14	N.O. Aux		140M-C, D, F	140M-C-AFA20
		O	X	O	23-24	N.O. Aux			
		X	O	X	11-12	N.C. Aux		140M-C, D, F	140M-C-AFA02
		X	O	X	21-22	N.C. Aux			
	Right Side-Mounted Auxiliary Contact <ul style="list-style-type: none"> 2-pole Adds 9 mm to the width of the device Two per MPCB 	O	X	O	33-34	N.O. Aux		140M-C, D, F	140M-C-ASA20
		O	X	O	43-44	N.O. Aux			
		X	O	X	31-32	N.C. Aux		140M-C, D, F	140M-C-ASA02
		X	O	X	41-42	N.C. Aux			
		O	X	O	33-34	N.O. Aux		140M-C, D, F	140M-C-ASA11
		X	O	X	41-42	N.C. Aux			

* X = Contact Closed; O = Contact Open

‡