Overview

Aruba 500H Series Unified Hospitality Access Points

High-performance and cost-effective Wi-Fi 6 (802.11ax) for hospitality, branch, and teleworker deployments

These economical Wi-Fi 6 access points provide high-performance connectivity for any organization experiencing growing mobile, cloud and IoT requirements. With a wireless aggregate data rate of up 1.5 Gbps and gigabit local wired ports, they deliver the range of connectivity options needed for venues such as hotels, residence halls, and remote offices alike.





Standard Features

Key Features

- Combine wireless and wired access in a single compact form-factor
- Up to 1.5 Gbps of maximum wireless throughput
- Up to 4 wired network ports and 1 Smart Rate uplink port
- WPA3 and Enhanced Open security
- Built-in technology that resolves sticky client issues for Wi-Fi 6 and Wi-Fi 5 devices
- OFDMA and MU-MIMO for enhanced multi-user efficiency
- IoT-ready Bluetooth 5 and Zigbee support

Incredible Efficiency

The Aruba 500H Series Unified Hospitality Access Points are designed to optimize user experience by maximizing Wi-Fi efficiency and dramatically reducing airtime contention between clients.

Features include Orthogonal frequency-division multiple access (OFDMA), multi-user MIMO and cellular optimization. With up to 4 spatial streams (4SS) and 80MHz channel bandwidth, the Aruba 500H Series provides groundbreaking wireless capabilities for budget-conscious deployments.

Read the Multi-User 802.11ax white paper for further information.

Advantages of OFDMA

This capability allows Aruba's APs to handle multiple Wi-Fi 6 capable clients on each channel simultaneously, regardless of device or traffic type. Channel utilization is optimized by handling each transaction via smaller sub-carriers or resource units (RUs), which means that clients are sharing a channel and not competing for airtime and bandwidth.

Aruba Air Slice for Extended OFDMA Assurance

APs in controller-less mode (Instant) can provide SLA-grade performance by allocating RUs to specific traffic types. By combining Aruba's Policy Enforcement Firewall (PEF) and Layer 7 deep packet inspection (DPI) to identify user roles and applications, the APs will dynamically allocate the bandwidth needed. Non-Wi-Fi 6 clients can also benefit. Air Slice for APs in controller mode will be supported in a future software release. Learn more in the technical brief.

Multi-user MIMO (MU-MIMO)

Similar to downlink MU-MIMO in Wi-Fi 5 (802.11ac Wave 2), the Aruba 500H Series Unified Hospitality Access Points can simultaneously connect clients using downlink – and now – uplink spatial streams. The added benefit is the ability to multiply the number of clients that can now send traffic, thus optimizing client-to-AP spatial stream diversity.

Wi-Fi 6 and MU-MIMO aware client optimization

Aruba's patented AI-powered ClientMatch technology eliminates sticky client issues by placing Wi-Fi 6 capable devices on the best available AP. Session metrics are used to steer mobile devices to the best AP based on available bandwidth, types of applications being used and traffic type – even as users roam.

Advanced Cellular Coexistence (ACC)

This feature uses built-in filtering to automatically minimize the impact of interference from cellular networks, distributed antenna systems (DAS), and commercial small cell or femtocell equipment.

Intelligent Power Monitoring (IPM)

Aruba APs continuously monitor and report hardware energy consumption. They can also be configured to enable or disable capabilities based on available PoE power – ideal when wired switches have exhausted their power budget.

Green AP energy efficiency

Aruba Wi-Fi 6 APs can use analytics from Aruba Central to automatically transition in and out of a sleep mode based on client density.



Standard Features

IoT Platform Capabilties

Like all Aruba Wi-Fi 6 APs, the Aruba 500H Series includes an integrated Bluetooth 5 and 802.15.4 radio (for Zigbee support) to simplify deploying and managing IoT-based location services, asset tracking services, security solutions and IoT sensors. This allows organizations to leverage the Aruba 500H Series as an IoT platform, which eliminates the need for an overlay infrastructure and additional IT resources.

Target Wake Time (TWT)

Ideal for IoTs that communicate infrequently, TWT establishes a schedule for when clients need to communicate with an AP. This helps improve client power savings and reduces airtime contention with other clients.

Advanced IoT Coexistence (AIC)

This features uses built-in filtering to automatically minimize the impact of interference from IoT wireless radios like Bluetooth and Zigbee.

Aruba Secure Infrastructure

The Aruba 500H Series Unified Hospitality Access Points includes components of Aruba's 360 Secure Fabric to help protect user authentication and wireless traffic.

WPA3 and Enhanced Open

Support for stronger encryption and authentication is provided via the latest version of WPA for enterprise protected networks. Enhanced Open offers seamless new protection for users connecting to open networks where each session is automatically encrypted to protect user passwords and data on guest networks.

WPA2-MPSK

MPSK enables simpler passkey management for WPA2 devices – should the Wi-Fi password on one device or device type change, no additional changes are needed for other devices. This requires ClearPass Policy Manager.

VPN Tunnels

In Remote AP (RAP) and IAP-VPN deployments, the Aruba 500H Series can be used to establish a secure SSL/IPSec VPN tunnel to a Mobility Controller that is acting as a VPN concentrator.

Trusted Platform Module (TPM)

For enhanced device assurance, all Aruba APs have an installed TPM for secure storage of credentials, keys, and boot code.

Simple and Secure Access

To simplify policy enforcement, the Aruba 500H Series uses Aruba's Policy Enforcement Rirewall (PEF) to encapsulate all traffic from the AP to the mobility controller (or gateway) for end-to-end encryption and inspection. Policies are applied based on user role, device type, applications, and location. This reduces the manual configuration of SSIDs, VLANs and ACLs. PEF also serves as the underlying technology for Aruba Dynamic Segmentation.

High-Density Connectivity

Each Aruba 500H Series AP provides connectivity for a maximum of 256 associated clients per radio (512 in total). In real-world scenarios, the maximum recommended client density is dependent on environmental conditions.

Versatile Installation Options

The APs can be deployed as a wall-mount or, for remote teleworker environments, they can be converted to a desk-mount by using an optional accessory stand.

Flexible Operation and Management

A unique feature of Aruba APs is the ability to operate in either controller-less (Instant) or controller-based mode.

Standard Features

Controller-less (Instant) mode

In controller-less mode, one AP serves as a virtual controller for the entire network. Learn more about Instant mode in **this technology brief**.

Mobility Controller mode

For optimized network performance, roaming and security, APs tunnel all traffic to a mobility controller for centrally managed traffic forwarding and segmentation, data encryption, and policy enforcement. Learn more in the ArubaOS datasheet.

Management options

Available management solutions include Aruba Central (cloud-managed) or Aruba AirWave – a multi-vendor on-premises management solution.

For large installations across multiple sites, APs can be factory-shipped and can be activated with Zero Touch Provisioning through Aruba Central or AirWave. This reduces deployment time, centralizes configuration, and helps manage inventory.

Aruba 500H Remote AP bundles

To simplify the ordering and distribution of Aruba 500H Series Unified Hospitality Access Points, we offer a number of AP bundles that combine an AP variant a desk stand, power adapter, and North American or European power cord. This makes it easier to get remote workers and small branches up and running quickly.

Additional Wi-Fi Features

Each AP also includes the following standards-based technologies:

- Advanced Cellular Coexistence (ACC) minimizes the impact of interference from cellular networks
- Advanced IOT Coexistence (AIC) allows concurrent operation of multiple radios in the 2.4GHz band
- Maximum ratio combining (MRC) for improved receiver performance
- Cyclic delay/shift diversity (CDD/CSD) for improved downlink RF performance
- Space-time block coding (STBC) for increased range and improved reception
- Low-density parity check (LDPC) for high-efficiency error correction and increased throughput
- Transmit beam-forming (TxBF) for increased signal reliability and range
- 802.11ax Target Wait Time (TWT) to support low-power client devices

Configuration Information

Build To Order: BTO is a standalone unit with no integration. BTO products ship standalone are not part of a CTO or Rack-Shippable solution.

Shippable		
BTO Mo	dels	
Remarks	Description	SKU
	Aruba AP-503H	
Notes:	Add Mount Kit (not included)	
	Aruba AP-503H (EG) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V44A
	Aruba AP-503H (IL) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V42A
	Aruba AP-503H (JP) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V40A
	Aruba AP-503H (RW) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V36A
	Aruba AP-503H (US) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V38A
	Aruba AP-503HR	
Notes:	Bundle includes Mount Kit, Power Supply and Power Cord	
	Aruba AP-503HR (EU) Remote AP bundle with AP-503H (RW) + desk mount + power adapter + EU power cord	R7G96A
	Aruba AP-503HR (US) Remote AP bundle with AP-503H (US) + desk mount + power adapter + NA power cord	R7G97A
	Aruba AP-505H	
Notes:	Add Mount Kit (not included)	
	Aruba AP-505H (EG) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V54A
	Aruba AP-505H (IL) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V52A
	Aruba AP-505H (JP) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V50A
	Aruba AP-505H (RW) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V46A
	Aruba AP-505H (US) Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V48A
	Aruba AP-505HR	
Notes:	Bundle includes Mount Kit, Power Supply and EU Power Cord	
	Aruba AP-505HR (EU) Remote AP bundle with AP-505H (RW) + desk mount + power adapter + EU power cord	R3V56A
Notes:	Bundle includes Mount Kit, Power Supply and US Power Cord	
	Aruba AP-505HR (US) Remote AP bundle with AP-505H (US) + desk mount + power adapter + NA power cord	R3V57A
	Aruba AP-503H TAA	
Notes:	Add Mount Kit (not included)	
	Aruba AP-503H (EG) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V45A
	Aruba AP-503H (IL) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V43A
	Aruba AP-503H (JP) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V41A
	Aruba AP-503H (RW) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V37A
	Aruba AP-503H (US) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+2 Ethernet	R3V39A
	Aruba AP-505H TAA	
Notes:	Add Mount Kit (not included)	
	Aruba AP-505H (EG) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V55A
	Aruba AP-505H (IL) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V53A
	Aruba AP-505H (JP) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V51A
	Aruba AP-505H (RW) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB	R3V47A
Notor	Aruba AP-505H (US) TAA Dual-radio 802.11ax 2x2 Unified Hospitality AP with 1+4 Ethernet PSE USB OCA Only Model Selection Form ->Aruba > Wireless > Access Points > Hospitality / Remote:>Aruba	R3V49A
Notes:	500H Series Unified Hospitality Access Points	

Configuration Information

Mount Accessories

	Aruba AP-Mount Kits	
1, 2, 3	AP-500H-MNT1 Kit with Single-gang Wall-box Mount Adapter for 500H Series AP	R3V58A
Notes:	For wall and (wiring) wall-box	
1, 3	AP-505H-MNT2 Kit with Dual-gang Wall-box Mount Adapter for AP-505H	R3V59A
Notes:	For wall and (wiring) wall-box	
2, 3 Notes:	AP-500H-MNTD Kit with Desk Mount Adapter for 500H Series AP For desk	R3V60A
1, 2, 3	AP-503H-MNT2 Kit with Dual-gang Wall-box Mount Adapter for AP-503H	R3V61A
Notes:	For wall and (wiring) wall-box	NO VOLA
1, 2, 3	Aruba AP-500H-MNTD2 RJ45 Ethernet Jack Desk Mount	SOJ41A
Notes:	For desk	0001117
	Configuration Rules	
Rule#	Description	SKU
1	For Aruba 503H Series Std (Min 0 // max 1) User Selection (min 1 // max 1)	
2	For Aruba 505H Series Std (Min 0 // max 1) User Selection (min 1 // max 1)	
3	For Aruba 503HR/505HR Series Std (Min 0 // max 0) User Selection (min 0 // max 0)	
Power C	Options	
Rule #	Description	SKU
	Power Options	
Notes:	Most devices are PoE powered from switch so these are optional	
1, 2, 4	AP-AC2-12B 12V/48W AC/DC desktop style power adapter with 2.1/5.5mm connector	R3K00A
	Add AC power cord, Unrestricted	
1, 3, 4	AP-AC2-48C 48V/50W AC/DC desktop style power adapter with 1.35/3.5mm connector	R3K01A
	Add AC power cord, Unrestricted	
1, 2, 3, 4	AP-POE-AFGE 1-Port GbE 802.3af 15.4W midspan injector	R6P68A
	Add AC Power Cord, Unrestricted(AP-503H)	
1, 3, 4	AP-POE-ATSR 1-Port Smart Rate 802.3at 30W midspan injector	R6P67A
1, 3, 4	AP-POE-BTSR 1-Port Smart Rate 802.3bt 60W midspan injector	R1C73A
, -,	Add AC power cord, Unrestricted	
	Configuration Rules	
Rule#	Description	SKU
1	If this Power Supply is selected, bring in (Min 1 // Max 1) Localized power cord based on the Aruba	
	Localization Menu	
2	For Aruba 503H Series Std (Min 0 // max 1) User Selection (min 0 // max 1)	
3	For Aruba 505H Series Std (Min 0 // max 1) User Selection (min 0 // max 1)	
4	For 503HR/505HR Series Std (Min 0 // max 0) User Selection (min 0 // max 0)	

Accessories

Other Accessories

For Aruba 503H/505H Series Std (Min 0 // max 99) User Selection (min 0 // max 99)	
For Aruba 503HR/505HR Series Std (Min 0 // max 99) User Selection (min 0 // max 99)	
AP-CBL-SERU Micro-USB TTL3.3V to USB2.0 AP Console Adapter Cable	JY728A
AP-MOD-SERU Micro-USB TTL3.3V to RJ45 RS232 AP Console Adapter Module	R6Q99A



Configuration Information

	Aruba AP-MC-SFP Media Converter Module for WLAN Access Points (SFP with DC to Copper with POE)	R8F89A
	Aruba USB LTE Modem for use with Access Points and Gateways	R8F34A
	Aruba USB Extender Cable Kit for use with Aruba USB LTE Modem	R8G76A
Notes:	Drivers available on the Aruba Support Center	
Softwar	e	
Remarks	Description	SKU
	Aruba Central AP Foundation 1 year Subscription E-STU	Q9Y58AAE
	Aruba Central AP Foundation 3 year Subscription E-STU	Q9Y59AAE
	Aruba Central AP Foundation 5 year Subscription E-STU	Q9Y60AAE
	Aruba Central AP Foundation 7 year Subscription E-STU	Q9Y61AAE
	Aruba Central AP Foundation 10 year Subscription E-STU	Q9Y62AAE
	Aruba Central AP Advanced 1yr Subscription E-STU	Q9Y63AAE
	Aruba Central AP Advanced 3yr Subscription E-STU	Q9Y64AAE
	Aruba Central AP Advanced 5yr Subscription E-STU	Q9Y65AAE
	Aruba Central AP Advanced 7yr Subscription E-STU	Q9Y66AAE
	Aruba Central AP Advanced 10yr Subscription E-STU	Q9Y67AAE
Notes:	Add the Central Cloud Skus to the Aruba Catalog as Standalone:	
	Aruba > Network Management > Central > Cloud Services	
	Aruba Central On-Premises AP Foundation 1 year Subscription E-STU	R6U63AAE
	Aruba Central On-Premises AP Foundation 3 year Subscription E-STU	R6U64AAE
	Aruba Central On-Premises AP Foundation 5 year Subscription E-STU	R6U65AAE
	Aruba Central On-Premises AP Foundation 7 year Subscription E-STU	R6U66AAE
	Aruba Central On-Premises AP Foundation 10 year Subscription E-STU	R6U67AAE
Notes:	Add the Central On-Prem Skus to the Aruba Catalog as Standalone:	
	Aruba > Network Management > Central > On-Prem Services	

Hardware Variants

- Aruba AP-503H: Mid-range dual radio Wi-Fi 6 Hospitality AP with 1+2 Ethernet ports
- Aruba AP-505H: High-end dual radio Wi-Fi 6 Hospitality AP with 1+4 Ethernet ports, PSE, USB

Dimensions and weight Aruba AP-503H

- Unit by itself:
 - 86mm (W) x 47mm (D) x 150mm (H)
 - 360g
- Unit in shipping box:
 - 111mm (W) x 54mm (D) x 167mm (H)
 - 450g

Aruba AP-505H

- Unit by itself:
 - 86 (W) x 47 (D) x 150 mm (H) / 3.4 (W) x 1.9 (D) x 5.9 in (H)
 - 360 gm / 0.8 lb
- Unit in shipping box:
 - 111 (W) x 54 (D) x 167 mm (H) / 4.4 (W) x 2.1 (D) x 6.6 in (H)
 - 450 gm / 1.0 lb

Wi-Fi Antennas

- Aruba AP-503H:
 - Two integrated semi-directional antennas for 2x2 MIMO with peak single antenna gain of 5.2dBi in 2.4GHz and 5.4dBi in 5GHz. Built-in antennas are optimized for vertical wall or desk mounted orientation of the AP.
 - Combining the patterns of each of the antennas of the MIMO radios, the peak gain of the combined, average pattern is 1.7dBi in 2.4GHz and 5.0dBi in 5GHz.
- Aruba AP-505H:
 - Two integrated semi-directional antennas for 2x2 MIMO with peak antenna gain of 6.3dBi in 2.4GHz and 5.4dBi in 5GHz. Built-in antennas are optimized for vertical wall or desk mounted orientation of the AP.
 - Combining the patterns of each of the antennas of the MIMO radios, the peak gain of the combined, average pattern is 3.3dBi in 2.4GHz and 2.9dBi in 5GHz.

Crypto Performance

- Aruba AP-503H: VPN IPsec throughput performance: 100Mbps or better
- Aruba AP-505H: VPN IPsec throughput performance: 500Mbps or better.

Regulatory Model Numbers

- Aruba AP-503H (all variants) APINH503
- Aruba AP-505H (all variants) APINH505

Mounting

• Optional mounting kits: Using one of the (separate orderable) mount kits, the AP can be attached to a single or dual gang wall-box, directly to a wall, or desk mounted. See the Aruba 500H Series Ordering Guide for details.



WI-FI Radio Specifications

5 GHz

• Two spatial stream (SU/MU) MIMO for up to 1.2Gbps wireless data rate

2.4 GHz

- Two spatial stream (SU/MU) MIMO for up to 287Mbps wireless data rate
 Notes: HE40 operation is supported in 2.4GHz, but uncommon and not recommended for enterprise deployments
- Support for up to 256 associated client devices per radio, and up to 16 BSSIDs per radio
- Supported frequency bands (country-specific restrictions apply):
- 2.400 to 2.500GHz (ISM), channels 1-13
 - 5.150 to 5.250GHz (U-NII-1), channels 36, 40, 44, 48
 - 5.250 to 5.350GHz (U-NII-2A), channels 52, 56, 60, 64
 - 5.470 to 5.725GHz (U-NII-2C), channels 100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140, 144
 - 5.725 to 5.850GHz (U-NII-3), channels 149, 153, 157, 161, 165
 - 5.850 to 5.925GHz (U-NII-4), channels 169, 173, 177
- Dynamic frequency selection (DFS) optimizes the use of available RF spectrum
- Supported radio technologies:
 - 802.11b: Direct-sequence spread-spectrum (DSSS)
 - 802.11a/g/n/ac: Orthogonal frequency-division multiplexing (OFDM)
- 802.11ax: Orthogonal frequency-division multiple access (OFDMA) with up to 8 resource units (RU)
- Supported modulation types:
 - 802.11b: BPSK, QPSK, CCK
 - 802.11a/g/n: BPSK, QPSK, 16-QAM, 64-QAM, 256-QAM (proprietary extension)
 - 802.11ac: BPSK, QPSK, 16-QAM, 64-QAM, 256-QAM, 1024 QAM (proprietary extension)
 - 802.11ax: BPSK, QPSK, 16-QAM, 64-QAM, 256-QAM , 1024 QAM
- 802.11n high-throughput (HT) support: HT 20/40
- 802.11ac very high throughput (VHT) support: VHT 20/40/80
- 802.11ax high efficiency (HE) support: HE20/40/80
- Supported data rates (Mbps):
 - 802.11b: 1, 2, 5.5, 11
 - 802.11a/g: 6, 9, 12, 18, 24, 36, 48, 54
 - 802.11n: 6.5 to 300 (MCS0 to MCS15, HT20 to HT40) , 400 with 256-QAM
 - 802.11ac: 6.5 to 867 (MCSO to MCS9, NSS = 1 to 2 for VHT20 to VHT160), 1,083 with 1024-QAM
 - 802.11ax (2.4GHz): 3.6 to 574 (MCSO to MCS11, NSS = 1 to 2, HE2O to HE4O)
 - 802.11ax (5GHz): 3.6 to 1,201 (MCS0 to MCS11, NSS = 1 to 4, HE20 to HE80)
- 802.11n/ac packet aggregation: A-MPDU, A-MSDU
- Transmit power: Configurable in increments of 0.5 dBm
- Maximum (aggregated, conducted total) transmit power (limited by local regulatory requirements):
 - 2.4 GHz band: +21 dBm (18 dBm per chain)
 - 5 GHz band: +21 dBm (18 dBm per chain)
 - Notes: conducted transmit power levels exclude antenna gain
- Minimum configurable transmit power level: OdBm (conducted, per chain)

Certifications

- Wi-Fi Alliance:
 - Wi-Fi CERTIFIED™ a, b, g, n, ac
 - Wi-Fi CERTIFIED™ 6 (ax)
 - WPA, WPA2 and WPA3 Enterprise with CNSA option, Personal (SAE), Enhanced Open (OWE)
 - WMM, WMM-PS, Wi-Fi Vantage, Wi-Fi Agile Multiband
 - Passpoint (release 2)
 - Bluetooth SIG (Aruba AP-505H only)
- Ethernet Alliance (POE, PD device, class 6)

Additional interfaces

- Aruba AP-503H:
 - Uplink (E0): Ethernet wired network port (RJ45)
 - o Auto-sensing link speed (10/100/1000BASE-T) and MDI/MDX
 - o 802.3az Energy Efficient Ethernet (EEE)
 - o POE-PD: 802.3af POE (class 3)
 - Local (E1-E2): Two Ethernet wired network ports (RJ45)
 - o Auto-sensing link speed (10/100/1000BASE-T) and MDI/MDX
 - o 802.3az Energy Efficient Ethernet (EEE)
 - DC power interface: 12Vdc (nominal, +/- 5%), accepts 2.1mm/5.5mm center-positive circular plug with 9.5mm length
 - Aruba AP-505H:
 - EO: HPE SmartRate port (RJ-45)
 - o Auto-sensing link speed (100/1000/2500BASE-T) and MDI/MDX
 - o 2.5Gbps speed complies with NBase-T and 802.3bz specifications
 - o 802.3az Energy Efficient Ethernet (EEE)
 - E1-4: 10/100/1000BASE-T (RJ-45)
 - o Auto-sensing link speed and MDI/MDX
 - o 802.3az Energy Efficient Ethernet (EEE)
 - E1-2: POE-PSE, 48Vdc (nominal) 802.3af/at POE output (max 30W combined)
 - DC power interface: 48Vdc (nominal, +/- 5%), accepts 1.35mm/3.5mm center-positive circular plug with 9.5mm length
 - Bluetooth Low Energy (BLE5.0) and Zigbee (802.15.4) radio
 - BLE: up to 7dBm transmit power (class 1) and -100dBm receive sensitivity (125kbps)
 - Zigbee: up to 7dBm transmit power and -98dBm receive sensitivity (250kbps)
 - Integrated semi-directional antenna with peak gain of 1.2dBi
 - USB 2.0 (Type A):
 - Cellular modems
 - IOT or other plug-in accessories
 - Device battery charging port
 - Capable of sourcing up to 1A / 5W to an attached device
 - Visual indicators (2 multi-color LEDs):
 - Power/System status
 - Radio status
 - Local network port status (4x)
 - POE-PSE status (2x)
 - Serial console interface: proprietary, micro-B USB physical jack
 - Security slot: Kensington security slot

Regulatory

- FCC/ISED
- CE Marked
- RED Directive 2014/53/EU
- EMC Directive 2014/30/EU
- Low Voltage Directive 2014/35/EU
- IEC/EN 60950
- EN 60601-1-1, EN60601-1-2
- IEC/EN 62368-1

For more country-specific regulatory information and approvals, please see your Aruba representative.



Power

- Supports direct DC power and Power over Ethernet (PoE)
- When both DC and PoE power sources are available, DC power takes priority over PoE
- Power sources are sold separately; see the Aruba 500H Series Ordering Guide for details
- Aruba AP-503H:
 - When powered by DC or 802.3af (class 3) POE, the AP will operate without restrictions.
 - Maximum (worst-case) power consumption:
 - o DC powered: 14W
 - o POE powered (802.3af): 13.5W
 - Maximum (worst-case) power consumption in idle mode: 6.2W
 - Maximum (worst-case) power consumption in deep-sleep mode: 3.5W
- Aruba AP-505H:
 - When powered by DC or 802.3bt (class 6) PoE, the AP will operate without restrictions.
 - When powered by 802.3at (class 4) PoE and with the IPM feature disabled, the AP will disable the USB port (only) if PoE-PSE is enabled and limit PoE-PSE power to 12.5W. In the same configuration but with IPM enabled, the AP will (only) limit PoE-PSE power to 15.4W (802.3af class 3), but may dynamically apply additional restrictions depending on the PoE budget and actual power. The feature restrictions and order can be programmed.
 - Maximum (worst-case) power consumption (without USB or PSE / max):
 - o DC powered: 12W / 50W
 - o PoE powered (802.3bt): 12W / 50W
 - o PoE powered (802.3at): 12W / 25.5W
 - o PoE powered (802.3af): 12W / 13.5W
 - Maximum (worst-case) power consumption in idle mode: 6W (DC) or 6W (PoE)
 - Maximum (worst-case) power consumption in deep-sleep mode: 3W (DC) or 3W (PoE)

Environmental

- Operating:
 - Temperature: -0° C to +40° C (+32° F to +104° F)
 - Humidity: 5% to 93% non-condensing
 - ETS 300 019 class 3.2 environments
- Storage and transportation:
 - Temperature: -40° C to +70° C (-40° F to +158° F)
 - Humidity: 5% to 93% non-condensing
 - ETS 300 019 classes 1.2 and 2.3 environments

Warranty

Limited lifetime warranty

Minimum Operating System Software

• ArubaOS and Aruba InstantOS 8.7.1.0 (Aruba AP-503H) and 8.7.0.0 (Aruba AP-505H)

	Maximum transmit power (dBm) per	Receiver sensitivity (dBm) per	
	transmit chain	receive chain	
2.4GHz, 802.11b			
1Mbps	18	-98	
11Mbps	18	-90	
2.4GHz, 802.11g			
5Mbps	18	-93	
54Mbps	18	-76	
2.4GHz, 802.11n HT20			
MCSO	18	-93	
MCS7	16	-75	
2.4GHz, 802.11ax HE20			
MCSO	18	-93	
MCS11	14	-62	
5GHz, 802.11a			
6Mbps	18	-92	
54Mbps	18	-75	
5GHz, 802.11n HT20			
MCSO	18	-92	
MCS7	16	-74	
5GHz, 802.11n HT40			
MCSO	18	-90	
MCS7	16	-71	
5GHz, 802.11ac VHT20			
MCSO	18	-90	
MCS9	16	-69	
5GHz, 802.11ac VHT40	10		
MCS0	18	-90	
MCS9	16	-65	
5GHz, 802.11ac VHT80	10		
MCS0	18	-87	
MCS9	16	-62	
5GHz, 802.11ax HE20	10	02	
MCS0	18	-93	
MCS11	14	-62	
5GHz, 802.11ax HE40		02	
MCS0	18	-90	
MCSU MCS11	18	-59	
	14	-2-	
5GHz, 802.11ax HE80 MCS0	18	-87	

Notes: Table shows the maximum capability of the hardware provided (excluding antenna gain). Maximum transmit power is limited by local regulatory settings.



Summary of Changes

Date	Version History	Action	Description of Change
06-Mar-2023	Version 10	Changed	Configuration Information section was updated.
21-Nov-2022	Version 9	Changed	Updates worked through out the document.
15-Aug-2022	Version 8	Changed	Configuration Information section was updated.
05-Jul-2022	Version 7	Changed	Configuration Information section was updated, new SKUs were added.
06-Dec-2021	Version 6	Changed	SKUs were added in Configuration Information section was updated.
15-Mar-2021	Version 5	Changed	Configuration Information section was updated.
01-Feb-2021	Version 4	Changed	Configuration Information section was updated.
04-Jan-2021	Version 3	Changed	Standard Features and Configuration Information sections were updated. New SKUS were added.
08-Sep-2020	Version 2	Changed	Configuration Information section was updated. New SKUS were added.
04-May-2020	Version 1	New	New QuickSpecs

Copyright

Make the right purchase decision. Contact our presales specialists.

Chat now (sale	s)
Call now	
Get up	dates

© Copyright 2023 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.



To learn more, visit: http://www.hpe.com/networking

a00056117enw - 16331 - Worldwide - V10 - 06-March-2023